

## Thanos KNX FAQ

1. Which software is needed to configure thanos KNX ?
  - ETS3/ETS4 via "Parameter"
2. Which ETS version is required?
  - At least ETS3.0f (Build 00990)
  - ETS4.1.4 (Build 3109)
  - ETS5.0.6 (Build1267)
3. Where can I obtain information on the connection diagram/firmware?
  - Please have a detailed look at the data sheet
4. Where can I get the project files from?
  - <https://www.thermokon.de/downloadcenter/#>  
Room Operating Units -> Premium Design -> thanos -> Software -> thanos KNX Version 2.4. zip
5. How can I import the project data files in ETS?
  - ETS5 - "project import"
  - ETS4 - project view "Import"
  - ETS3 - file "Import"
  - Afterwards "open project/ administer..."
6. Which file ending is for which ETS version?
  - ETS3 project file: \*.pr5
  - ETS4 project file: \*.knxproj
  - ETS4 project file: \*.knxproj
7. I need a product file with the ending (\*.knxprod, \*.vd5, \*.vd4, \*.vd3, \*.vd2, \*.vd1, \*.vdx). Where can I get the same?
  - At the moment no product files are available
  - Please work with the project files \*.pr5 or \*.knxproj
8. How can I integrate a thanos KNX device into an existing project?
  - Open the imported thanos KNX project as well as the existing project
  - Device can only be copied from one to another project by "Drag&Drop"
9. Which physical address does thanos KNX have upon delivery?
  - 1.15.255
10. Where can I find the programming button for programming a new physical address?
  - The touching keys over the clip, lower edge on the left side and upper edge on the right side, must be pressed at the same time for approx. 10 seconds (L-type).
  - The touching keys on the right hand side of the clip, lower edge on the left side and upper edge on the right side, must be pressed at the same time for approx. 10 seconds (LQ-type).
11. Do I need a SD-card to install the Thanos KNX?
  - No, the SD card is only necessary to make a firmware update.
12. Where is the current firmware version displayed?
  - When starting thanos KNX the current firmware version number is displayed

13. Which firmware must be available to work with the current project files?
- Firmware Net Unit (KNX) 2.4.0
14. Thanos KNX displays „Bus Unit: 1.2/KNX“ after power start. Can I make a firmware update?
- No, this version is a customized software version which does not allow any updates via the SD card.
15. How does Thanos KNX produced before 07.11.2012 differ from the current devices?
- As for older devices, the connectors 2,3,4,5 are backed out at the back side of the product
  - New devices additionally have the connectors 6,7,8,9,10 backed at the back side because they have 4 digital inputs, too.